



Product: 2003 HP LaserJet 2300 Series Printer Service Repair Workshop Manual
Full Download: <https://www.arepairmanual.com/downloads/2003-hp-laserjet-2300-series-printer-service-repair-workshop-manual/>



hp LaserJet 2300
series printer



service



Sample of manual. Download All 296 pages at:
<https://www.arepairmanual.com/downloads/2003-hp-laserjet-2300-series-printer-service-repair-workshop-manual/>

Product: 2003 HP LaserJet 2300 Series Printer Service Repair Workshop Manual
Full Download: <https://www.arepairmanual.com/downloads/2003-hp-laserjet-2300-series-printer-service-repair-workshop-manual/>

Sample of manual. Download All 296 pages at:
<https://www.arepairmanual.com/downloads/2003-hp-laserjet-2300-series-printer-service-repair-workshop-manual/>

hp LaserJet 2300 series printer

service manual _____

© Copyright Hewlett-Packard
Company, 2003

All Rights Reserved.
Reproduction, adaptation, or
translation without prior written
permission is prohibited, except
as allowed under the copyright
laws.

Part number: Q2472-90908

Edition 1, April 2003

Warranty

The information contained in this
document is subject to change
without notice.

Hewlett-Packard makes no
warranty of any kind with respect
to this information. HEWLETT-
PACKARD SPECIFICALLY
DISCLAIMS THE IMPLIED
WARRANTY OF
MERCHANTABILITY AND
FITNESS FOR A PARTICULAR
PURPOSE.

Hewlett-Packard shall not be
liable for any direct, indirect,
incidental, consequential, or
other damage alleged in
connection with the furnishing or
use of this information.

Trademark credits

Adobe® and PostScript® are
trademarks of Adobe Systems
Incorporated which may be
registered in certain jurisdictions.

UNIX® is a registered trademark
of the Open Group.

ENERGY STAR® is a U.S.
registered service mark of the
United States Environmental
Protection Agency.



Contents

1 Product description

Printer configurations	16
Printer features	17
Identification	19
Specifications	20
Physical specifications	20
Electrical specifications	20
Power consumption	20
Acoustic emissions	21
Operating environment	21
Product overview	22
Safety information	23
Print-cartridge and toner safety	23
Laser safety	24
Regulatory information	24
FCC regulations	24
Declaration of conformity	24
Environmental product stewardship program	25
Protecting the environment	25
Material safety data sheet	26
HP Printing Supplies Environmental Program information	26
Service approach	27
Bench-repair warranty	27
HP Express Exchange	27
Information about ordering	27
World Wide Web	28
HP service parts-information compact disc	28
HP support-assistant compact disc	28
Reseller sales and service support	28

2 Installation

Site requirements	30
Operating environment	30
Printer space requirements	31
Interface ports	33

Media specifications	34
General media specifications	34
Media input options	35
Tray 1 media sizes	35
Optional 250-sheet tray (tray 2 or tray 3) paper sizes	36
Optional 500-sheet tray (tray 3) paper sizes	37
Paper sizes for automatic duplexing	37
Guidelines for selecting paper	38
Envelope specifications	39
Label specifications	41
Transparency specifications	42
Storing print media	43
Shipping print media	43
Paper fillers	43
Testing media specifications	44
Tools and suppliers	49

3 Operation

Control panel	52
Control-panel layout	52
Changing control-panel settings	54
Printing control-panel menus	54
Control-panel menus—user	55
Retrieve job menu	55
Information menu	56
Paper-handling menu	57
Configure device menu	59
Diagnostics menu	71
Control-panel menus—service	72
Entering service mode	72

4 Printer maintenance

Periodic inspection of parts	74
Cleaning the printer	75
Cleaning the fuser	76
Cleaning the outside of the printer	76
Managing the print cartridge	77
HP print cartridges	77
Non-HP print cartridges	77
Print-cartridge authentication	77
Print-cartridge storage	78
Print-cartridge life expectancy	78
Checking the supply level	79
Cartridge-low and cartridge-out conditions	80
Supplies status page	81

5 Theory of operation

Introduction	84
Basic sequence of operation	84
Power-on sequence	85
Engine control system	86
Laser/scanner system	87
Image-formation system	88
Image-formation process	89
Electrostatic latent-image-formation block	90
Developing block	91
Transfer block	92
Fusing block	93
Drum-cleaning block	94
Pickup/feed system	95
Single-sided printing	95
Duplex printing	95
Delivery	97
Automatic duplexer	98
Formatter system	99
Formatter hardware	100
Formatter subsystem	101
Sheet feeders	103
Media detection	105
Media-size detection	105
Jam detection	106
Pickup sensors	106
Delivery sensors	107
Reversing sensors	107
Automatic duplexer sensors	108
Paper-feed sensor	108

6 Removal and replacement

Removal and replacement strategies	111
Required tools	111
Before you begin	112
Covers	113
I/O cover	113
Print server	114
DIMM cover	115
Rear cover	116
Front cover	119
Control panel	120
Top-cover assembly	121
Left-side cover	124
Power switch	125
Tray 1 assembly	126
Internal assemblies	130
Tray 1 pickup roller	130
Pickup sensor flag	132
Tray 1 separation pad	133
Tray 2 pickup roller	136
Tray 2 and 250-sheet feeder separation pad	139
Fan	140
Fuser	141
Laser/scanner	143
Laser/scanner plate	144
E-label reader	145
Formatter	147
Drive assembly	148
Main motor	151
Flat, flexible cable	152
Engine controller PCA	153
Solenoid	158
Access plate	159
Power supply	162
Top-output-bin delivery assembly	169
Registration-roller assembly	172
Transfer roller	174
Feed belts	175
Trays	176
250-sheet feeder and 500-sheet feeder pickup roller	176
500-sheet feeder separation pad	178

7 Troubleshooting

Troubleshooting process	180
Preliminary operating checks	180
Basic fault isolation	180
Troubleshooting process flow	182
Power-on	183
Troubleshooting with control-panel messages	184
Using the printer online Help system	184
Resolving persistent messages	184
Troubleshooting the control-panel display	185
Interpreting control-panel messages	186
Media-handling problems	199
Printing a configuration page	199
Printing a Jetdirect configuration page	200
Printing a usage page	201
Printing a supplies status page	201
Printing an engine test	202
Jam troubleshooting	204
Jam causes	205
Typical jam locations	205
Image-formation troubleshooting	210
Check the print cartridge	211
EconoMode	211
Image defects unique to the HP LaserJet 2300 series printers	211
Image-defect tables	212
Media troubleshooting	218
Determine the problem source: print media or printer	218
Isolate a paper path	218
Isolate a media brand	219
Isolate a media type	220
Evaluate media use practices	224
Evaluate environmental conditions	224
Communication troubleshooting	226
Communications check	226
Test message	226
EIO troubleshooting	226
Troubleshooting tools	227
Repetitive defect ruler	227
Half-self-test functional check	228
Performing a self test	229
Performing a paper path test	229
Drum-rotation functional check	229
Resetting the printer	230
Setting the language	230
Reference diagrams	231

8 Parts and diagrams

Ordering parts and supplies and getting support	242
Parts	242
Support	242
Consumables, accessories, and supplies	243
Common fasteners	244
Illustrations and parts lists	245
Assembly locations	245
Covers	246
Covers and panels	246
Top cover assembly	248
Internal components	250
Internal components (1 of 4)	250
Internal components (2 of 4)	252
Internal components (3 of 4)	254
Internal components (4 of 4)	256
Power-supply assembly	258
Pickup assembly	260
Engine controller	262
PCA locations	263
Trays	264
250-sheet feeder	264
500-sheet feeder	266
Alphabetical parts list	268
Numerical parts list	273

Figures

Figure 1.	Locations of identification labels	19
Figure 2.	Sample identification label	19
Figure 3.	Front and right side	22
Figure 4.	Back and left side	22
Figure 5.	Top view	31
Figure 6.	Side view.	31
Figure 7.	Side view (with an optional 250-sheet tray)	32
Figure 8.	Side view (with an optional 500-sheet tray)	32
Figure 9.	Interface ports	33
Figure 10.	Correct double side seam.	40
Figure 11.	Incorrect double side seam.	40
Figure 12.	Wet test for long, short, and diagonal grain curl	47
Figure 13.	Measuring curl	47
Figure 14.	Control-panel layout	52
Figure 15.	Supplies status page.	81
Figure 16.	Engine control system.	86
Figure 17.	Laser/scanner system.	87
Figure 18.	Image-formation system	88
Figure 19.	Image-formation system	89
Figure 20.	Step 1: primary charging.	90
Figure 21.	Step 2: laser-beam exposure	90
Figure 22.	Developing block.	91
Figure 23.	Step 3: developing	91
Figure 24.	Step 4: transfer	92
Figure 25.	Step 5: separation.	92
Figure 26.	Step 6: fusing	93
Figure 27.	Step 7: drum cleaning.	94
Figure 28.	Step 8: transfer charging roller cleaning	94
Figure 29.	Pickup/feed system	96
Figure 30.	Delivery.	97
Figure 31.	Automatic duplexer path	98
Figure 32.	Automatic duplexer feed and delivery.	98
Figure 33.	Pickup-feed paper path	103
Figure 34.	Sheet-feeder pickup and feed.	104
Figure 35.	Media-detection sensors.	105
Figure 36.	Removing the print cartridge.	112
Figure 37.	Removing tray 2	112
Figure 38.	Removing the I/O cover	113
Figure 39.	Removing the print server.	114
Figure 40.	Removing the DIMM cover	115
Figure 41.	Removing the rear cover (1 of 3)	116
Figure 42.	Removing the rear cover (2 of 3)	117
Figure 43.	Removing the rear cover (3 of 3)	118
Figure 44.	Removing the front cover	119
Figure 45.	Removing the control panel	120
Figure 46.	Removing the top-cover assembly (1 of 3)	121
Figure 47.	Removing the top-cover assembly (2 of 3)	122
Figure 48.	Removing the top-cover assembly (3 of 3)	123
Figure 49.	Removing the left-side cover	124
Figure 50.	Removing the power switch	125
Figure 51.	Removing the tray 1 assembly (1 of 4)	126
Figure 52.	Removing the tray 1 assembly (2 of 4)	127

Figure 53.	Removing the tray 1 assembly (3 of 4)	128
Figure 54.	Removing the tray 1 assembly (4 of 4)	129
Figure 55.	Removing the tray 1 pickup roller (1 of 2)	130
Figure 56.	Removing the tray 1 pickup roller (2 of 2)	131
Figure 57.	Removing the pickup sensor flag.	132
Figure 58.	Removing the tray 1 separation pad (1 of 3)	133
Figure 59.	Removing the tray 1 separation pad (2 of 3)	134
Figure 60.	Removing the tray 1 separation pad (3 of 3)	135
Figure 61.	Removing the tray 2 pickup roller (1 of 3)	136
Figure 62.	Removing the tray 2 pickup roller (2 of 3)	137
Figure 63.	Removing the tray 2 pickup roller (3 of 3)	138
Figure 64.	Removing the tray 2 and 250-sheet feeder separation pad.	139
Figure 65.	Removing the fan.	140
Figure 66.	Removing the fuser (1 of 2)	141
Figure 67.	Removing the fuser (2 of 2)	142
Figure 68.	Removing the laser/scanner	143
Figure 69.	Removing the e-label reader (1 of 3)	144
Figure 70.	Removing the e-label reader (2 of 3)	145
Figure 71.	Removing the e-label reader (3 of 3)	146
Figure 72.	Removing the formatter	147
Figure 73.	Removing the drive assembly (1 of 3)	148
Figure 74.	Removing the drive assembly (2 of 3)	149
Figure 75.	Removing the drive assembly (3 of 3)	150
Figure 76.	Removing the main motor	151
Figure 77.	Removing the flat, flexible cable	152
Figure 78.	Removing the engine controller PCA (1 of 5)	153
Figure 79.	Removing the engine controller PCA (2 of 5)	154
Figure 80.	Removing the engine controller PCA (3 of 5)	155
Figure 81.	Removing the engine controller PCA (4 of 5)	156
Figure 82.	Removing the engine controller PCA (5 of 5)	157
Figure 83.	Removing the solenoid	158
Figure 84.	Removing the access plate (1 of 3)	159
Figure 85.	Removing the access plate (2 of 3)	160
Figure 86.	Removing the access plate (3 of 3)	161
Figure 87.	Removing the power supply (1 of 6)	162
Figure 88.	Removing the power supply (2 of 6)	163
Figure 89.	Removing the power supply (3 of 6)	164
Figure 90.	Removing the power supply (4 of 6)	165
Figure 91.	Removing the power supply (5 of 6)	166
Figure 92.	Removing the power supply (6 of 6)	167
Figure 93.	Power-supply PCA spring-contacts	168
Figure 94.	Removing the top-output-bin-delivery assembly (1 of 3)	169
Figure 95.	Removing the top-output-bin delivery assembly (2 of 3)	170
Figure 96.	Removing the top-output-bin delivery assembly (3 of 3)	171
Figure 97.	Removing the registration-roller assembly (1 of 2)	172
Figure 98.	Removing the registration-roller assembly (2 of 2)	173
Figure 99.	Removing the transfer roller.	174
Figure 100.	Removing the feed belts	175
Figure 101.	Removing the pickup roller from a 250-sheet or 500-sheet feeder (1 of 2)	176
Figure 102.	Removing the pickup roller from a 250-sheet or 500-sheet feeder (2 of 2)	177
Figure 103.	Removing the 500-sheet feeder separation pad	178
Figure 104.	Troubleshooting process flow	182
Figure 105.	Control panel contrast label.	185
Figure 106.	Configuration page.	199
Figure 107.	Jetdirect configuration page.	200
Figure 108.	Engine test button	202
Figure 109.	Engine test page	203
Figure 110.	Image defects examples	212
Figure 111.	Repetitive defect ruler	227

Figure 112.	General printer-component locations	231
Figure 113.	Locations of switches	232
Figure 114.	Locations of sensors	233
Figure 115.	Locations of solenoid	234
Figure 116.	Location of motors and fans	235
Figure 117.	Engine controller PCB	236
Figure 118.	Power supply PCB	237
Figure 119.	General circuit diagram (1 of 2)	238
Figure 120.	General circuit diagram (2 of 2)	239
Figure 121.	General timing chart	240
Figure 122.	Assembly locations	245
Figure 123.	Covers and panels	246
Figure 124.	Top cover assembly	248
Figure 125.	Internal components (1 of 4)	250
Figure 126.	Internal components (2 of 4)	252
Figure 127.	Internal components (3 of 4)	254
Figure 128.	Internal components (4 of 4)	256
Figure 129.	Power-supply assembly	258
Figure 130.	Pickup assembly	260
Figure 131.	Engine controller	262
Figure 132.	PCA locations	263
Figure 133.	250-sheet feeder	264
Figure 134.	500-sheet feeder	266

Tables

Table 1.	Features for each configuration	18
Table 2.	Physical specifications	20
Table 3.	Electrical specifications.	20
Table 4.	Power specifications1	20
Table 5.	Acoustic emissions specifications1	21
Table 6.	Operating environment specifications.	21
Table 7.	Solutions for problem media.	38
Table 8.	Envelope specifications	39
Table 9.	Retrieve job menu.	55
Table 10.	Information menu	56
Table 11.	Paper-handling menu	57
Table 12.	Configure device menu—printing submenu	59
Table 13.	Configure device menu—print-quality submenu.	61
Table 14.	Configure device menu—system-setup submenu	64
Table 15.	Configure device menu—I/O submenu.	67
Table 16.	Configure device menu—resets submenu	70
Table 17.	Diagnostics menu	71
Table 18.	Service menu	72
Table 19.	Basic sequence of operation.	84
Table 20.	Output area jams recommended actions	206
Table 21.	Paper access area jams—recommended actions	207
Table 22.	Input-area jams.	208
Table 23.	Possible causes of frequent jams in the cartridge area	209
Table 24.	Image defects	213
Table 25.	Adhesive label construction	221
Table 26.	Envelope construction.	222
Table 27.	Technical support websites.	242
Table 28.	Consumables, accessories, and supplies.	243
Table 29.	Common fasteners	244
Table 30.	Covers and panels	247
Table 31.	Top cover assembly	249
Table 32.	Internal components (1 of 4).	251
Table 33.	Internal components (2 of 4).	253
Table 34.	Internal components (3 of 4).	255
Table 35.	Internal components (4 of 4).	257
Table 36.	Power-supply assembly	259
Table 37.	Pickup assembly.	261
Table 38.	Engine controller.	262
Table 39.	PCA locations	263
Table 40.	250-sheet feeder.	265
Table 41.	500-sheet feeder.	267
Table 42.	Alphabetical parts list	268
Table 43.	Numerical parts list	273

1

Product description

Chapter contents


Printer configurations	16
Printer features	17
Identification	19
Specifications	20
Physical specifications	20
Electrical specifications.	20
Power consumption	20
Acoustic emissions	21
Operating environment.	21
Product overview.	22
Safety information	23
Print-cartridge and toner safety	23
Laser safety	24
Regulatory information	24
FCC regulations	24
Declaration of conformity	24
Environmental product stewardship program	25
Protecting the environment.	25
Material safety data sheet.	26
HP Printing Supplies Environmental Program information	26
Bench-repair warranty	27
HP Express Exchange	27
Information about ordering	27
World Wide Web.	28
HP service parts-information compact disc	28
HP support-assistant compact disc	28
Reseller sales and service support.	28

Printer configurations

The HP LaserJet 2300 series printer is available in six configurations.


Note

The illustrations in this guide are based on the HP LaserJet 2300 printer model unless otherwise stated. To find out which HP LaserJet 2300 configuration you have, look at the label on the front of the printer.




HP LaserJet 2300L

The HP LaserJet 2300L printer prints letter-size paper at speeds up to 20 pages per minute (ppm) or A4-size paper at up to 19 ppm. It comes with a built-in 250-sheet tray, a parallel and a universal serial bus (USB) port, and 32 MB RAM. The printer is expandable, and has one available enhanced input/output (EIO) slot and two dual inline memory module (DIMM) slots for adding a network print server card, fonts, and memory.




HP LaserJet 2300

The HP LaserJet 2300 printer is the same as the HP LaserJet 2300L printer, except that it prints at speeds up to 25 ppm for letter-size paper and 24 ppm for A4-size paper.




HP LaserJet 2300d

The HP LaserJet 2300d printer is the same as the HP LaserJet 2300 printer, except that the printer comes with 48 MB RAM and automatically duplexes (prints on both sides of paper).



HP LaserJet 2300n

The HP LaserJet 2300n printer is the same as the HP LaserJet 2300 printer, except that it is designed for network users. It comes with a full-featured HP Jetdirect EIO print server card (for connecting to a 10/100Base-TX network) and 48 MB RAM.



HP LaserJet 2300dn

The HP LaserJet 2300dn printer is the same as the HP LaserJet 2300n printer, except that the printer also automatically duplexes (prints on both sides of paper).



HP LaserJet 2300dtn

The HP LaserJet 2300dtn printer is the same as the HP LaserJet 2300dn printer, except that it has an additional 500-sheet tray.

Printer features

The following table describes the features of the HP LaserJet 2300 series printers.

Fast print speed	<ul style="list-style-type: none">● The HP LaserJet 2300L prints on letter-size paper at speeds up to 20 pages per minute (ppm) or A4-size paper at up to 19 ppm.● All other models print on letter-size paper at speeds up to 25 ppm or A4-size paper at up to 24 ppm.
Built-in duplexing	<ul style="list-style-type: none">● Automatic two-sided (duplex) printing is a standard feature of the HP LaserJet 2300d, HP LaserJet 2300dn, and HP LaserJet 2300dtn printers.
Print cartridge and status features	<ul style="list-style-type: none">● The 6,000-page HP Smart Print Cartridge detects and reports toner status.● The no-shake design maximizes toner use.● The supplies status page provides a toner gauge, page count, and information about paper sizes that have been used.
Excellent print quality	<ul style="list-style-type: none">● FastRes 1200 produces 1200-dpi print quality for fast, high-quality printing of business text and graphics.● ProRes 1200 produces 1200-dpi printing for the best quality in line art and graphic images.● Adjustable settings optimize print quality.● The HP Smart Print Cartridge produces crisp, sharp output.
Flexible paper handling	<ul style="list-style-type: none">● Use tray 1 (the multipurpose tray) for letterhead, envelopes, labels, transparencies, custom-sized media, postcards, and heavy paper.● Use the adjustable 250-sheet tray (tray 2 or tray 3) for standard sizes of paper.● Use the 500-sheet tray (tray 3) for letter and A4-size paper.● Two output bins are available: select either the top output bin or the rear output bin for the most appropriate output location, depending on media type.● A straight-through paper path is available from tray 1 to the rear output bin.● Built-in automatic two-sided (duplex) printing is available for the HP LaserJet 2300d, HP LaserJet 2300dn, and HP LaserJet 2300dtn printers.
Expandability	<ul style="list-style-type: none">● A 250-sheet or 500-sheet tray is available, so that you do not have to add paper as often.● One EIO card slot is available for interface.● Three DIMM slots are available, two for adding memory and fonts.
Printer languages and fonts	<ul style="list-style-type: none">● Fast printing performance, advanced font and graphics technologies, and advanced imaging capabilities are benefits of the PCL 6 printer language. The PCL 6 technology also includes 45 scalable TrueType™ fonts and one bitmapped line printer font.● The other available languages and fonts are HP PCL5e and PostScript® (PS) 3 emulation, which includes 35 built-in PS language fonts.● The printer automatically determines and switches to the appropriate language for the print job.

Interface connections and networking	<ul style="list-style-type: none"> The printer includes a bidirectional ECP type-B parallel port (IEEE-1284 compliant) and a USB port (compatible with 1.1 and 2.0 low- and full-speed certified devices) The printer has an EIO slot for HP Jetdirect EIO print servers so that you can connect quickly and easily.
Enhanced memory and memory expansion	<ul style="list-style-type: none"> The HP LaserJet 2300 series printers come with either 32 MB or 48 MB of memory and can be expanded to 288 or 304 MB, respectively, with the available memory (DIMM) slots. Most documents can be printed by using the standard amount of printer memory.
Energy savings	<ul style="list-style-type: none"> The printer automatically conserves electricity by reducing power consumption when it is not printing. When the PowerSave feature is activated, the printer conserves energy when it is not in use. As an ENERGY STAR[®] partner, Hewlett-Packard Company has determined that this product meets ENERGY STAR[®] guidelines for energy efficiency.
Economical printing	<ul style="list-style-type: none"> N-up printing saves paper by printing multiple pages on one sheet of media. Automatic two-sided printing with the built-in duplexer saves paper (the built-in duplexer is included only with the HP LaserJet 2300d, HP LaserJet 2300dn, and HP LaserJet 2300dtn printers). Printing in EconoMode saves toner.

The table below gives a quick summary of the features for each model.

Table 1. Features for each configuration

Features	HP LaserJet 2300L	HP LaserJet 2300	HP LaserJet 2300n	HP LaserJet 2300d	HP LaserJet 2300dn	HP LaserJet 2300dtn
Standard memory	32 MB	32 MB	48 MB	48 MB	48 MB	48 MB
Maximum memory	288 MB	288 MB	304 MB	304 MB	304 MB	304 MB
PostScript 3 emulation	Standard	Standard	Standard	Standard	Standard	Standard
Automatic duplex printing	N/A	N/A	N/A	Standard	Standard	Standard
250-sheet feeder	Standard	Standard	Standard	Standard	Standard	Standard
500-sheet feeder	Optional	Optional	Optional	Optional	Optional	Standard

Identification

The model number and printer serial number are listed on identification labels located inside the top cover (callout 1) and on the rear output bin (callout 2).




Figure 1. Locations of identification labels

The model number is alphanumeric. The serial number contains information about the country of origin, as well as the revision level and the production code of the printer. An example of a serial number is USBB123456.

The identification label on the back of the printer also contains power rating and regulatory information. See figure 2.

Note The power rating and regulatory information vary by country/region.




Figure 2. Sample identification label

Specifications

Physical specifications

Table 2. Physical specifications

	HP LaserJet 2300L, 2300, 2300n, 2300d, 2300dn	HP LaserJet 2300dtn (with 500-sheet tray)
Height	259.7 mm (10.2 inches)	397.2 mm (15.6 inches)
Width	412.8 mm (16.2 inches)	412.8 mm (16.2 inches)
Depth (body)	450 mm (17.7 inches)	450 mm (17.7 inches)
Weight (with print cartridge)	14.3 kg (31.6 lb)	18.9 kg (41.6 lb)

Electrical specifications

WARNING!

Power requirements are based on the country/region where the printer is sold. Do not convert operating voltages. This can damage the printer and void the product warranty.

Table 3. Electrical specifications

Electrical specifications	110-volt models	220-volt models
Power requirements	110 to 127 V (+/- 10%) 50/60 Hz (+/- 3 Hz)	220 to 240 V (+/- 10%) 50/60 Hz (+/- 3 Hz)
Minimum recommended circuit capacity	5.0 amps	2.5 amps

Power consumption

Table 4. Power specifications¹

Product model	Average power consumption (in watts)				
	Printing (20 ppm)	Printing (25 ppm)	Standby	PowerSave²	Off
HP LaserJet 2300L	394 W	—	8.8 W	8.6 W	0 W
HP LaserJet 2300	—	426 W	8.8 W	8.4 W	0 W
HP LaserJet 2300n	—	426 W	9.6 W	9.3 W	0 W
HP LaserJet 2300d	—	426 W	8.8 W	8.4 W	0 W
HP LaserJet 2300dn	—	426 W	9.6 W	9.3 W	0 W
HP LaserJet 2300dtn	—	426 W	9.6 W	9.3 W	0 W

¹ Values are subject to change. See <http://www.hp.com/support/lj2300> for current information.

² The PowerSave default activation time is 15 minutes.

Acoustic emissions

Table 5. Acoustic emissions specifications¹

Sound power level	Declared per ISO 9296
Printing (HP LaserJet 2300L at 20 ppm)	$L_{WA_d} = 6.6$ bels(A)
Printing (all other models at 25 ppm)	$L_{WA_d} = 6.7$ bels(A)
PowerSave/standby ² (all models)	Inaudible
Sound pressure level, bystander position	Declared per ISO 9296
Printing (HP LaserJet 2300L at 20 ppm)	Inaudible
Printing (all other models at 25 ppm)	$L_{pAm} = 52$ dB(A)
PowerSave/standby ² (all models)	Inaudible
Sound pressure level, operator position	Declared per ISO 9296
Printing (HP LaserJet 2300L at 20 ppm)	Inaudible
Printing (all other models at 25 ppm)	$L_{pAm} = 59$ dB(A)
PowerSave/standby ² (all models)	Inaudible

¹ Values are subject to change. See <http://www.hp.com/support/lj2300> for current information.

² In standby, no mechanical parts are moving and therefore no sounds are made.

Operating environment

Table 6. Operating environment specifications

Environmental condition	Printing	Storage/standby
Temperature (printer and print cartridge)	15 to 32.5 degrees C (59 to 90.5 degrees F)	-20 to 40 degrees C (-4 to 104 degrees F)
Relative humidity	10 to 80 percent	10 to 90 percent

Product overview




Figure 3. Front and right side




Figure 4. Back and left side

Safety information

Print-cartridge and toner safety

For information about print-cartridge and toner safety, see the Toner Cartridge Material Safety Data Sheet (MSDS), which can be obtained at <http://www.hp.com/go/msds>.

Handling and storage

WARNING!

Keep print cartridges and toner particles away from excessive heat, sparks, and open flames.

If toner is spilled, avoid breathing in toner particles. Inhalation of toner particles causes respiratory-tract irritation. Vacuum or sweep the material into a bag or other sealed container. A vacuum specifically designed for cleaning toner can be used if it is capable of filtering fine particles (5 microns in diameter).

WARNING!

Do not vacuum toner using a conventional vacuum. Toner particles used in this product might be too fine for effective vacuuming and could result in damage to a conventional vacuum.

Dispose of waste toner in accordance with local requirements. Do not discharge toner particles in drains.

First aid measures

- **Ingestion.** If you ingest toner, rinse your mouth out thoroughly with water and drink several glasses of water. Get medical attention if symptoms occur.
- **Inhalation.** If you inhale toner particles, move to fresh air immediately. If symptoms occur, consult a physician.
- **Eye contact.** If toner comes in contact with your eyes, immediately flush the eyes with plenty of water for at least 15 minutes. If irritation persists, consult a physician.
- **Skin contact.** If toner spills on your skin, remove as much toner as possible with a dry tissue, and then wash with cold water.

Clothing contact

Note

Toner can stain clothing. Hot water or heat (such as heat from a clothes dryer) can cause toner to melt and permanently fuse to clothing.

Clothing is best cleaned by removing as much toner as possible with a dry tissue, and then washing with cold water. Air-dry the clothing.

Laser safety

The Center for Devices and Radiological Health (CDRH) of the U.S. Food and Drug Administration has implemented regulations for laser products manufactured since August 1, 1976. Compliance is mandatory for products that are marketed in the United States. The printer is certified as a Class 1 laser product under the U.S. Department of Health and Human Services (DHHS) Radiation Performance Standard according to the Radiation Control for Health and Safety Act of 1968.

Because radiation emitted inside the printer is completely confined within protective housings and external covers, the laser beam cannot escape during any phase of normal user operation.

CAUTION

Using controls, making adjustments, bypassing safety switches, or performing procedures other than those specified in this service manual can result in exposure to hazardous radiation.

Regulatory information

For regulatory information and requirements, please see the user guide.

FCC regulations

For FCC regulations, please see the user guide.

Declaration of conformity

For the declaration of conformity, please see the user guide.

Environmental product stewardship program

Protecting the environment

Hewlett-Packard Company is committed to providing quality products in an environmentally sound manner. This product has been designed with several attributes that minimize impacts on our environment.

Ozone production

This product generates no appreciable ozone gas (O₃).

Energy consumption

Energy usage drops significantly while the printer is in PowerSave mode, which saves natural resources and saves money without affecting the performance of the printer. This product qualifies for ENERGY STAR[®], a voluntary program established to encourage the development of energy-efficient office products.



ENERGY STAR[®] is a U.S. registered service mark of the United States Environmental Protection Agency. As an ENERGY STAR[®] partner, Hewlett-Packard Company has determined that this product meets the ENERGY STAR[®] guidelines for energy efficiency. For more information, see <http://www.epa.gov/energystar/>.

Toner consumption

EconoMode uses significantly less toner, which might extend the life of the print cartridge.

Paper use

This product's automatic two-sided (duplex) printing feature and n-up printing capability (multiple pages printed on one sheet of paper) can reduce paper usage and the resulting demands on natural resources.

Plastics

Plastic parts more than 25 grams in weight are marked according to international standards that enhance the ability to identify plastics for recycling purposes at the end of the product's life.

HP LaserJet printing supplies

In many countries/regions, this product's printing supplies (for example, the print cartridge, drum, and fuser) can be returned to HP through the HP Printing Supplies Returns and Recycling Program. An easy-to-use takeback program is available in more than 48 countries/regions. Multilingual program information and instruction are included in every new HP LaserJet print cartridge and consumables package.

Paper

This printer is suited for the use of recycled papers when the paper meets the guidelines outlined in the *HP LaserJet Printer Family Print Media Guide*. Also, this printer is suitable for the use of recycled paper according to DIN 19309.

Material safety data sheet

Material safety data sheets (MSDS) can be obtained by contacting the HP LaserJet Supplies website at <http://www.hp.com/go/msds> .

HP Printing Supplies Environmental Program information

Since 1990, the HP Printing Supplies Returns and Recycling Program has collected millions of used LaserJet print cartridges that otherwise might have been discarded in the world's landfills. The HP LaserJet print cartridges and consumables are collected and bulk-shipped to our resource and recovery partners, who disassemble the cartridges for recycling. After a thorough quality inspection, selected parts are reclaimed for use in new cartridges. Remaining materials are separated and converted into raw materials for use by other industries to make a variety of useful products.

U.S. returns

For a more environmentally-responsible return of used cartridges and consumables, HP encourages the use of bulk returns. Simply bundle two or more cartridges together and use the single, pre-paid, pre-addressed UPS label that is supplied in the package. For more information, call (1) (800) 340-2445 or visit the HP LaserJet Supplies website at <http://www.hp.com/recycle> .

Non-U.S. returns

Customers should call their local HP sales and service office or visit <http://www.hp.com/recycle> for information regarding availability of the HP Supplies Returns and Recycling Program.

Service approach

Bench-repair warranty

The warranty for this product is “return to bench” for a period of one year from the date of purchase. This means that customers who need warranty repair must return their printer to an HP repair center or an Authorized Service Provider (ASP). See “Reseller sales and service support” on page 28.

HP Express Exchange

Through Customer Care Centers in the United States and Canada, customers have an option to initiate Express Exchange. Under this option, customers can have a factory-refurbished printer sent to them within 24 hours.

- 1 The customer contacts the local HP Customer Care Center listed in the product documentation. A technician troubleshoots the situation and determines whether the printer has actually failed. If so, the technician refers the customer to the HP Service Center.
- 2 A representative from the service center requests product and customer information. In some regions, collateral might also be requested.
- 3 Hewlett-Packard Company ships a refurbished replacement unit to arrive the next day. (Geographic distance might prevent next-day shipping.)
- 4 The customer sends the defective printer to Hewlett-Packard at HP's expense.

Customers with onsite support service provided by HP should work directly with the local Customer Care Center instead of following the steps outlined here.

Exchanged units carry the remainder of the original unit's warranty or a 90-day warranty, whichever is greater. The faster turnaround from HP Express Exchange minimizes downtime over traditional service programs that require the user to ship the failed unit to the manufacturer and then wait for it to be repaired and returned. Because HP pays the shipping charges, the user incurs no hidden costs for the service.

Note

For warranty information and requirements, please see the user guide.

Information about ordering

"Ordering parts" in chapter 8 of this manual contains factory-replacable unit (FRU) and accessory part numbers. Replacement parts can be ordered from the HP Customer Services and Support Organization.

Use only accessories that are specifically designed for this printer. Order accessories from an authorized service or support provider.

Product: 2003 HP LaserJet 2300 Series Printer Service Repair Workshop Manual

Full Download: <https://www.arepairmanual.com/downloads/2003-hp-laserjet-2300-series-printer-service-repair-workshop-manual/>

Printer drivers, updated HP printer software, and product and support information can be obtained from the following URL:

in the U.S., <http://www.hp.com/support/lj2300>

Printer drivers can be obtained from the following sites:

- China, <ftp://www.hp.com.cn/support/lj2300>
- Japan, <ftp://www.jpn.hp.com/support/lj2300>
- Korea, <http://www.hp.co.kr/support/lj2300>
- Taiwan, <http://www.hp.com.tw/support/lj2300>
or the local driver website, <http://www.dds.com.tw>

HP service parts-information compact disc

This powerful, CD-ROM-based parts-information tool is designed to give users fast, easy access to parts information, such as pricing and recommended stocking lists, for a wide range of HP products. To subscribe to this quarterly service in the U.S. or Canada, call (1) (800) 336-5987. In Asia Pacific countries/regions, call (65) 740-4484. Parts identification and pricing information can also be found on the World Wide Web at <http://www.hp.com/go/partsinfo>.

HP support-assistant compact disc

This support tool offers a comprehensive online information system that is designed to provide technical and product information about Hewlett-Packard products. To subscribe to this quarterly service in the U.S. or Canada, call (1) (800) 457-1762. In Hong Kong SAR, Indonesia, Malaysia, or Singapore, call Mentor Media at (65) 740-4477.

Reseller sales and service support

The HP Customer Care Center is available to assist resellers and service technicians. You can reach this support center in the U.S. or Canada by calling (1) (800) 544-9976.

HP authorized resellers and support

To locate authorized HP resellers and support, call (1) (800) 243-9816 in the U.S. or (1) (800) 387-3867 in Canada.

HP service agreements

Call (1) (800) 743-8305 in the U.S. or (1) (800) 268-1221 in Canada.

Other areas

Outside of North America and Europe, contact your local HP sales office for assistance in obtaining technical support for resellers and service technicians.

Sample of manual. Download All 296 pages at:

<https://www.arepairmanual.com/downloads/2003-hp-laserjet-2300-series-printer-service-repair-workshop-manual/>